



HP Cluster Configuration Support Matrix For Microsoft Windows 2000 Advanced Server & HP StorageWorks MSA500 G2

Config	Supported Servers	Server Software	Host Bus Adapters (HBAs)	Multipath Software	Storage Information	Other
#1 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> • DL360 G3, DL360 G4, DL360 G4p SCSI, DL360 G4p SATA, DL360 G4p SAS • DL380 G3, DL380 G4, DL380 G4 SAS • DL385, DL385 SAS • DL560 • DL580 G2, DL580 G3, DL580 G3 SAS • DL585, DL585 SAS • DL740 • DL760 G2 • ML350 G3, ML350 G4, ML350 G4p, ML350 G4p SAS • ML370 G3, ML370 G4, ML370 G4 SAS • ML530 G2 • ML570 G2, ML570 G3, ML570 G3 SAS 	SmartStart Ver: 7.70	Smart Array 642 Driver: 5.74.0.32 FW: 2.68 Smart Array 6i * Driver: 5.74.0.32 FW: 2.68 *Note: only used with the DL360 G4 and DL380 G4 servers.	Smart Array Multipath Software Ver: 2.0d	StorageWorks MSA500 G2 Storage Controller FW: 1.56 Storage EMU FW: 2.28 on 2-port 2.30 on 4-port Array Configuration Utility Ver: 7.60.18.0 or later	Product Page Supporting Documentation January 2007
#2 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> • DL360 G3, DL360 G4, DL360 G4p SCSI, DL360 G4p SATA, DL360 G4p SAS • DL380 G3, DL380 G4, DL380 G4 SAS • DL385, DL385 SAS • DL560 • DL580 G2, DL580 G3, DL580 G3 SAS • DL585, DL585 SAS • DL740 • DL760 G2 • ML350 G3, ML350 G4, ML350 G4p, ML350 G4p SAS • ML370 G3, ML370 G4, ML370 G4 SAS • ML530 G2 • ML570 G2, ML570 G3, ML570 G3 SAS 	SmartStart Ver: 7.4 utilized with PSP 7.40A	Smart Array 642 Driver: 5.68.0.32 FW: 2.58 Smart Array 6i * Driver: 5.68.0.32 FW: 2.58 *Note: only used with the DL360 G4 and DL380 G4 servers.	Smart Array Multipath Software Ver: 2.0b	StorageWorks MSA500 G2 Storage Controller FW: 1.52 Storage EMU FW: 2.28 on 2-port 2.30 on 4-port Array Configuration Utility Ver: 7.15.19.0	Product Page Supporting Documentation MSCS Support Matrix - Archive December 2005
#3 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> • DL360 G3, DL360 G4 • DL380 G3, DL380 G4 • DL560 • DL580 G2 • DL585 • DL740 • DL760 G2 • ML350 G3, ML350 G4 • ML370 G3, ML370 G4 • ML530 G2 • ML570 G2 	SmartStart Ver: 7.1 utilized with PSP 7.10A	Smart Array 642 Driver: 5.62.0.32 FW: 2.26 Smart Array 6i * Driver: 5.62.0.32 FW: 2.26 *Note: only used with the DL360 G4 and DL380 G4 servers.	Smart Array Multipath Software Ver: 2.0b	StorageWorks MSA500 G2 Storage Controller FW: 1.40 Storage EMU FW: 2.28 on 2-port 2.30 on 4-port Array Configuration Utility Ver: 7.15.19.0	Product Page Supporting Documentation MSCS Support Matrix - Archive September 2004

<p>#4</p> <p>Windows 2000 Advanced Server</p> <p>Service Pack 4</p>	<p>Max supported nodes = 2</p> <p>ProLiant:</p> <ul style="list-style-type: none"> • DL360 G3 • DL380 G3 • DL560 • DL580 G2 • DL740 • DL760 G2 • ML350 G3 • ML370 G3 • ML530 G2 • ML570 G2 	<p>SmartStart</p> <p>Ver: 7.0 utilized with PSP 7.00A</p>	<p>Smart Array 642</p> <p>Driver: 5.50.0.32</p> <p>FW: 1.92</p>	<p>Smart Array Multipath Software</p> <p>Ver: 2.0a</p>	<p>StorageWorks MSA500 G2</p> <p>Storage Controller FW: 1.14</p> <p>Storage EMU FW: 1.92 on 2-port and 4-port modules</p> <p>Array Configuration Utility</p> <p>Ver: 7.10.5.0</p>	<p>Product Page</p> <p>Supporting Documentation</p> <p>MSCS Support Matrix - Archive</p> <p>May 2004</p>
---	--	---	---	--	---	--