



HP Cluster Configuration Support Matrix For Microsoft Windows 2000 Advanced Server & HP StorageWorks RA4100

Config	Supported Servers*	Server Software	Host Bus Adapters (HBAs)	Multi Path Software	Storage Information	Interconnects (Switches)	Other
#1 Windows 2000 Advanced Server Service Pack 4	<ul style="list-style-type: none"> • W2K Max supported nodes = 2 ProLiant <ul style="list-style-type: none"> • DL360, DL360 G2, DL360 G3 • DL380, DL380 G2, DL380 G3 • DL560 • DL580, DL580 G2 • DL740 • DL760, DL760 G2 • ML370, ML370 G2, ML370 G3 • ML530, ML530 G2 • ML570, ML570 G2 • ML750 • PL1850R • PL6400R • PL6500 • PL8000 • PL8500 <p>* Note: Servers can be used homogeneously or heterogeneously within a cluster.</p>	SmartStart Ver: 6.4 (Install non-RBSU servers using SmartStart 5.5 and then apply PSP 6.4)	<ul style="list-style-type: none"> • 64-bit/66-Mhz Fibre Channel Host Adapter (Persian) cpqfcac driver ver: 5.20.0.32 cpqfcalm driver ver: 5.30.0.32 cpqfcftr driver ver: 5.20.0.32	StorageWorks Secure Path Ver: 3.1A for Windows for RA4100 Service Pack 1 w/ Registry Patch for Secure Path 3.1A for Windows for RA4100 (ver. 2.11.15.0) Raidisk.sys ver: 3.2.0.17 Rdful.sys ver: 3.1.0.6	StorageWorks RA4100 Storage Controller FW: v2.60	HP StorageWorks SAN Switches (1GB) FW: 2.60h <ul style="list-style-type: none"> • SAN Switch 16-EL • SAN Switch 8-EL • SAN Switch 8 & 16 Other Switches and Hubs <ul style="list-style-type: none"> • 7-port FC-AL hub • FC-AL Switch 8 FW: V120G12 from Softpaq SP16384	Product Page Supporting Documentation MSCS Support Matrix - archive

August 2003