


**EM100 FX** 

Fast Fiber Ethernet LAN Adapter




- Supports 100 Mbits/sec. IEEE 802.3u 100BASE-FX Standard
- DECchip® 21140 LAN coprocessor chip
- 132 MByte/sec. burst data rate across the PCI bus for maximum performance
- Full flexibility, with versions for both ST (twist-on) and SC (push-on) connectors
- Predictive Pipelining<sup>™</sup> for greater throughput with lower CPU utilization
- Full Duplex Fast Ethernet (FDFE) capability for up to 200 Mbits/sec. performance
- Cabling distances of up to 400 meters in half-duplex and 2 kilometers in Full Duplex
- All popular networks supported
- Comprehensive setup and diagnostics utility
- Limited lifetime warranty





EM100 FX is the first Fast Ethernet PCI adapter to support the IEEE 100BASE-FX (fiber optic cabling) standard. The fiber optic interface makes EM100 FX ideal for use in 'electrically noisy' environments such as building risers and factory floors, and also in backbone environments where longer cabling distances are required. For maximum throughput, EM100 FX includes Full Duplex Fast Ethernet (FDFE) capability, which doubles the cumulative system throughput rate in switched or dedicated backbone environments. FDFE capability is easily enabled via software configuration.



# LAN Adapter

# Extended distance with familiar technology

Using the familiar Fast Ethernet standard, EM100 FX can extend networks to 400 meters in half-duplex, and 2 kilometers in Full Duplex (200 Mbits/sec.), mode. EM100 FX lets you leverage the large bandwidth and distance potential of fiber optic cabling using the same Ethernet packets you are already using; costly FDDI to Ethernet protocol translations are no longer necessary.

# **Connector Options**

The EM100 FX achieves universal fiber optic cable connectivity by providing either an ST (twist-on) connector, for preexisting fiber optic cable and connectors, or the newer SC (push-on) connector, for newer cable installations. Both interfaces use the same multimode fiber cabling and support Full Duplex operation.

## High bandwidth networking

Ten times faster than traditional 10 Mbits/sec. Ethernet adapters, EM100 FX Fast Ethernet is ideal for resource-intensive graphics, multimedia, Microsoft Windows, and mission-critical applications, which need high throughput and low CPU utilization to power large amounts of data across the network.

Cogent offers Ethernet products to meet every adapter and repeater environment, including 10BASE-2, 10BASE-T, 100BASE-TX, 100BASE-T4, and 100BASE-FX (fiber).

# **Product Specifications**

## Systems Supported

PCI Local Bus computers, based on Intel, DEC Alpha, MIPS, and PowerPC processors

#### Bus Interface

PCI, 32-bit bus master

#### **Ethernet Controller**

DECchip® 21140 LAN coprocessor chip

#### Hardware Interrupts

PCI interrupt A supports shared interrupts

#### Base I/O Address

Assigned by BIOS

## PCI Configuration Space

Supports DWORD, WORD, and BYTE access

## Reliability

Calculated MTBF >100,000 hours

## **Power Requirements**

+5 volts @ 1.5 Amp. max

## **Environmental Operating Range**

Temperature: 0° C to 50° C Relative Humidity: 5% to 85% non-condensing Altitude: 3000m maximum

#### Interface Connections

Supports 62.5/125 micron multimode fiber ST (twist-on) SC (push-on)

#### Maximum Cabling Distance

400 meters half-duplex 2 kilometers Full Duplex

#### **Dimensions**

5.075" x 3.9" (conforms to PCI Short Card specification)

#### Standards Compliance

IEEE 802.3u 100BASE-FX

#### Drivers Available

3.5" diskette
NetWare 3.x, 4.x, NetWare Lite, Personal
NetWare, LAN Manager, VINES, IBM LAN
Server, OS/2 Warp, Artisoft LANtastic, Windows
for Workgroups, DEC PATHWORKS for DOS,
FTP PC/TCP, LAN Workplace for DOS, ODI
Windows NT for Intel, DEC Alpha, MIPS,
PowerPC, Windows 95, Windows for
Workgroups 3.11

### Diagnostic LEDs

Link Integrity, Network Activity

## Warranty

All emaster+ series adapters are protected by a limited lifetime warranty

#### Ordering Information

Order Number Connectors
EM100FX-PCI-ST ST
EM100FX-PCI-SC SC

Made in U.S.A.

Your local Cogent dealer is:

#### Cogent Sales

15375 SE 30th Place, Suite 310 Bellevue, WA 98007 U.S.A. Tel (206) 603-0333 Toll-free in U.S. 1-800-426-4368 Fax (206) 603-9223 E-mail sales@cogentdata.com

### **Cogent Corporate**

640 Mullis Street Friday Harbor, WA 98250 U.S.A. Tel (360) 378-2929 Fax (360) 378-2882 URL http://www.cogentdata.com

#### Cogent Europe

Rosenstraße 7 80331 Munich Germany Tel [49] 89/231138-88 Fax [49] 89/231138-11

